


Thomson SpeedTouch 536 Realm Change Guide.

1. Start your Internet Browser and in the address bar type the following IP address
http://192.168.1.254/ewizard.htm
2. The Welcome to SpeedTouch Easy Setup screen appears. No changes are required, click **Next**.
3. The Service Selection screen appears. No changes are required, click **Next**.
4. The Routed Internet Connection screen appears as below. Delete all of the letters to the right of the "@" symbol, replace them with **talktalkbb** Then enter your broadband password in the password field, click **Next**.

Routed Internet Connection

Specify the details of your Internet connection. All information should be provided by your ISP.



VPI/VCI
Select VPI/VCI (UK Default 0.38)

Connection Type
 PPPoA (UK Default)
 PPPoE

User Name

Enter your Internet connection user name.

Password

Enter your Internet connection password (if required).

5. The Start Configuration screen appears. No changes are required, click **Start**.
6. Your broadband modem will restart automatically. Please allow up to **5 minutes** for this to happen. After the modem has restarted, you will be shown a connection status screen similar to the screenshot below, stating that you have successfully completed the Setup. Click **Finish**.



Completing the SpeedTouch™ Easy Setup

You have successfully completed the SpeedTouch™ Easy Setup.

To close Easy Setup, click Finish.