

Thomson SpeedTouch 585 Realm Change Guide.

1. Start your Internet Browser and in the address bar type the following IP address
<http://192.168.1.254/ewizard.htm>
2. If prompted for login details, enter the following details and click **OK**.
User Name: **admin**
Password: **[This is the serial number located on the bottom of the modem]**
3. *If you previously changed the router configuration password, use the password you set instead.
4. The Welcome to SpeedTouch Easy Setup screen appears. No changes are required, click **Next**.
5. The Service Selection screen appears. No changes are required, click **Next**.
6. The Routed Internet Connection screen appears as below. Delete all of the letters to the right of the "@" symbol, replace them with **talktalkbb** Then enter your broadband password in the password field, click **Next**.

Routed Internet Connection
Specify the details of your Internet connection. All information should be provided by your ISP.

VPI/VCI: 8.35
Select VPI/VCI (UK Default 0.38)

Connection Type:
 PPPoA (UK Default)
 PPPoE

User Name: TalkTalk12345@talktalkbb
Enter your Internet connection user name.

Password: [Masked]
Enter your Internet connection password (if required).

< Back Next > Cancel

7. The Wireless Security screen appears. No changes are required, click **Next**.
8. The Access Control screen appears. No changes are required, click **Next**.
9. The Start Configuration screen appears. No changes are required, click **Start**.
10. Your broadband modem will restart automatically. Please allow up to **5 minutes** for this to happen. After the modem has restarted, you will be shown a connection status screen similar to the screenshot below, stating that you have successfully completed the Setup. Click **Finish**.

THOMSON
imagine & beyond

Completing the SpeedTouch™ Easy Setup

You have successfully completed the SpeedTouch™ Easy Setup.

To close Easy Setup, click Finish.

< Back Finish Cancel